					Login F	Register English	0
Products	Solutions	Design	Buy	Support	About Us	My Maxim	
Maxim > Products >	<u>i</u> Button® Devices > DS1961S						
DS1961S							
1Kb Pro	tected EEPRO	OM <u>i</u> Button v	with SHA-	I Engine			
World-Class S	Security in Stainless Ste	el Case for Access	Control and eCas	h Applications			
Overview	Technical Documents O	rdering Info Related I	Products User Co	mments (0) All			
Status 🧧					Data Sheet		
Part Number	Status				Request Full Data Sheet		
DS1961S	Active: In Production. See Ordering Information for details.						
Description	ı						
The DS1961S co user read/write b	ombines 1024 bits of EEPR oytes, a 512-bit SHA-1 engined serially via the 1-Wire pr	OM, a 64-bit secret, an ne and a fully featured 1	8-byte register/contr -Wire® interface in a	ol page with up to five a rugged <u>i</u> Button®.			

Each DS1961S has its own 64-bit ROM registration number that is factory lasered into the chip to provide a guaranteed unique identity for absolute traceability. The durable stainless steel package is highly resistant to environmental hazards such as dirt, moisture, and shock. Its compact coin-shaped profile is self-aligning with mating receptacles, allowing the DS1961S to be easily used by human operators. Accessories permit the DS1961S to be mounted on almost any surface including plastic key fobs and photo-ID badges.

The DS1961S understands a unique command "Refresh Scratchpad." Proper use of a refresh sequence (see Writing with Verification section) after a copy scratchpad operation reduces the number of weak bit failures in a touch environment. The refresh sequence also provides a means to restore functionality in a device with bits

The DS1961S has an additional memory area called the scratchpad that acts as a buffer when writing to the main memory, the register page or when installing a new secret. Data is first written to the scratchpad from where it can be read back. After the data has been verified, a copy scratchpad command will transfer the data to its final memory location, provided that the DS1961S receives a matching 160-Bit message authentication code (MAC). The computation of the MAC involves the secret and additional data stored in the DS1961S including the device's Identity Register. Only a new secret can be loaded without providing a MAC. The SHA-1 engine can also be activated to compute 160-bit MAC when reading a memory page or to compute a new

Key Features

in a weak state

secret, instead of loading it.

- 1128 bits of 5V EEPROM memory partitioned into four pages of 256 bits, a 64-bit write-only secret and up to five general purpose read/write registers
- Write access requires knowledge of the secret and the capability of computing and transmitting a 160-bit MAC as authorization
- Secret and data memory can be write-protected (all or page 0 only) or put in EPROM-emulation mode ("write to 0", page 1)
- On-chip 512-bit SHA-1 engine to compute 160-bit MAC
 and to generate secrets
- Reads and writes over a wide voltage range of 2.8V to 5.25V from -40°C to +85°C
- Communicates to host with a single digital signal at 14.1kb per second using 1-Wire protocol
- On-chip 16-bit CRC generator for safeguarding data transfers
- Overdrive mode boosts communication speed to 125kbps
- Operating temperature range from -40°C to +85°C
- Minimum 10 years of data retention at 85°C

Common iButton Features

- Unique, factory-lasered and tested 64-bit registration number (8-bit family code + 48-bit serial number + 8-bit CRC tester) assures absolute traceability because no two parts are alike
- Multidrop controller for 1-Wire net

- Digital identification and information by momentary contact
- · Chip-based data carrier compactly stores information
- Data can be accessed while affixed to object
- Button shape is self-aligning with cup-shaped probes
- Durable stainless steel case engraved with registration number withstands harsh environments
- · Easily affixed with self-stick adhesive backing, latched by its flange, or locked with a ring pressed onto its rim
- · Presence detector acknowledges when reader first applies voltage

Key Specifications:

iButton Products Smallest Available Real **Budgetary Price** Part Memory Memory Security Unique Pckg. Applications Time Number Size Features Ware Type (mm²) Clock max w/pins See Notes Electronic SHA-1 DS1961S Access Control EEPROM 1K bits Write-Only No No 301 \$2.22 @1k Secrets eCash See All iButton Products (26)

Pricing Notes: This pricing is BUDGETARY, for comparing similar parts. Prices are in U.S. dollars and subject to change. Quantity pricing may vary substantially and international prices may differ due to local duties, taxes, fees, and exchange rates. For volume-specific prices and delivery, please see the price and availability page or contact an authorized distributor.

Diagram



More Information

New Product Press Release [2002-09-04]

Didn't Find What You Need?

Next Day Product Selection Assistance from Applications Engineers Parametric Search **Applications Help**

Information Index

Rev 3; 2009-09-02 This page last modified: 2011-04-04

Overview Description Key Features Applications/Uses **Key Specifications** Diagram Notes and Comments

Data Sheet Application Notes **Evaluation Kits Product Guides Reliability Reports** Software/Models

Technical Documents

Ordering Info Price and Availability Samples Buy Online Package Information

Lead-Free Information

Related Products Similar Products by Function Similar Products by Application Evaluation Kits Products with Similar Part Numbers Products Used With This

Contact Us | Privacy Policy | Legal Notices

Copyright © 2012 by Maxim Integrated Products